

DuraFon™ long range cordless

SN902 - 1x
SP922 - 4x
SP9228 - PRO

Product Features



Long Range coverage up to 12 Floors in building penetration for hotel or office building environment	Yes	Yes	Yes
Long Range coverage up to 250,000 sq. ft. in warehouse or manufacturing plant environment	Yes	Yes	Yes
Long Range coverage up to 3000 acres in farm or ranch environment	Yes	Yes	Yes
Lines / Ports per base unit	1	4	4
Line / Port expansion	1 - 4 (1 port per base)	4 (single base only)	4 - 32 (4 ports per base)
Two-way radio broadcast (half duplex) call to one handset, to a group or to all handsets	Yes	Yes	Yes
Two-way radio intercom (full duplex) - private call to other registered handsets. Independent of base	Yes	Yes	Yes
Works with any PBX phone system for wireless communication	Yes*	Yes*	Yes*
Base unit expansion	4	0	8
Eliminates monthly airtime fees or network access charges	Yes	Yes	Yes
Battery - charging time / standby time / talk time	3 / 50 / 6hrs	3 / 50 / 6hrs	3 / 50 / 6hrs
Built in spare battery charger slot	Yes	Yes	Yes
Hot swappable batteries	Yes	Yes	Yes
Durable handsets (drop tested on concrete floor)	Yes	Yes	Yes
Optional external antenna to enhance range	Yes	Yes	Yes
Handset expansion (with max base units)	36	90	90 +
Handset grouping (eg: sales group, management, parts department, security)	7	7	7
Secure and private communications via DSS and Frequency Hopping	Yes	Yes	Yes
Intercom from base	Yes	No	No
Line access - single handset can access multi lines	Yes**	Yes	Yes
Line dedication	Individual or Group	Individual or Group	Individual or Group
Non-conflicting wireless LAN frequency	Yes	Yes	Yes
Programmable PBX functions	9 per handset	9 per handset	9 per handset
Wireless PBX function copying - no need to manually program each handset	No	No	Yes
Wireless phonebook copying	No	No	Yes
Receive remote broadcast page through base	No	No	Yes
Speakerphone	Yes	No	Yes
Speed dial (phone / two-way)	Yes / No	Yes / Yes	Yes / Yes
Auto attendant for multi line call handling for home office, small business without a PBX	No	Yes	No

* Requires analog port

**Requires 2 base units